

Model : SQP2250 (S)

Standby Power (50Hz)	2250KVA/1800KW
Prime Power(50Hz)	2000KVA/1600KW

Standard Features

- Engine: Perkins 4016TAG2A
- Charge Alternator: 24V
- Governer: Electronic
- Generator: Stamford PI734F
- Single Bearing Alternator IP23
- Insulation Class H/H
- Genuine radiator with engine driven fan
- Skid and vibration isolators
- Dry type air filter
- Main line circuit breaker (Below 500KVA)
- 12V battery and cable
- User's manual



Weight And Dimensions

Genset	Dimensions(LxWxH)	Weight (KG)
Open type	4800mmx2200mmx2477mm	13875
Silent type	12192mmx2438mmx2896mm	21875

Generator Ratings

Voltage	Hz	Phase	Power Factor	Standby (KVA/KW)	Prime (KVA/KW)
400/230	50	3	0.8	2250/1800	2000/1600

Criterion

- Generator sets: GB/T2820-1997, ISO9001: 2008
- Alternator: BS5000, VDE0530, NEMA MG1-32, IEC34, CSAC22.2-100, AS1359
- Diesel Engine: ISO3046, DIN6271



Engine Data

• Manufacturer/Model	Perkins 4016TAG2A
• No.of Cylinders	16
• Displacement	61.123L
• Bore and Stroke	160*190(mm)
• Compression ratio	13.6:1
• Rated RPM	1500rpm
• Max.standby power at rated 1500RPM	1886KW
• Aspiration	Turbocharged
• Governor Type	Electronic
• Exhaust Gas Flow @Standby Rating	387m ³ /min
• Exhaust Temperature @Standby Rating	493°C
• Intake Air Flow@Standby Rating	145m ³ /min
• Fuel System	Direct injection
• 100%(Prime Power) Load	209Liter/H
• Lubrication System Min. capacity	147L
• Total Coolant Capacity	316L

Alternator Data

• Manufacture/Type	Stamford/PI734F
• Number of phase power	3
• Factor	0.8
• Pole Number	4
• Bearing Number	1
• Exciter Type	Brushless, self-excited
• Insulation Class	H/H
• Protection	IP23

Control Panel



- Auto Module Control Panel, usually adopt control module of UK Deepsea DSE 7320 or Equal, is the configuration for nobody on duty generators control, This kind of panel adopts auto module control system, with large LCD display to show the menu.
- Features: receive remote output signal from ATS and realize auto start and stop of generators.
- Auto Mains Failure controller, can realize further more can detect ATS and control directly.
- RS232 or 485 interface which can communicate with PC to realize remote operation.





- Automatic Parallel Control Panel usually adopting intelligent control module of UK Deepsea DSE8610 or equal, this new automatic parallel system is inserted and folded installed, no need the peripheral relay and logic circuit. The main switch adopts electronic breaker or frame breaker, combined together with the generator, which is very reliable. One generator, one panel. The panel can be used both for single genset working or Gensets Parallel working. This kind of panel also can be used to parallel generator when the capability of the power plant needs to be enlarged in the future.

Optional

Engine	Alternator	Fuel System	Control System
<ul style="list-style-type: none"> • Pre-heater 	<ul style="list-style-type: none"> • Anti Condensation Heater • Drop CT (For Paralleling) 	<ul style="list-style-type: none"> • Daily Fuel Tank • Water Separator 	<ul style="list-style-type: none"> • Remote Control Panel • Auto Transfer Switch (ATS) • Paralleling System • Electricity Output Cabinet

Others

- Rainproof Type
- Soundproof Type
- Trailer Type
- Container Type
- Spare Parts



Warranty



- Warranty is according to our standard conditions: 12 months or 1,200 running hours, subject to the earlier one. And what's more, Perkins gensets enjoy world-wide united Warranty from Perkins engine agency or service centre at the client's local side.
- Service and parts are available from Guangzhou Sanq Power Equipment Co.,Ltd or our distributors in your location.

